









## Unpacking

Before you begin using the device, please check the version you got and ensure that the following items are included in the shipped box:


-  Plastic wall anchor x 4
-  M4x30 crosshead screw x 2
-  10 Pin cable x 1  
(Except C313N)
-  11 Pin cable x 1
-  Wall-mounting bracket x 1
-  C313X x 1
-  ST4x20 crosshead screw x 2

## Product Overview

### Front View




### Rear View



NOTE: C313N does not have PON\_OUT Interface.

## Installation

### Without 86 embedded box in the wall




Mark two fixation holes through wall-mounting bracket on the wall, the distance between which is 60mm. Make sure the all cables can be passed from the middle of wall-mounting bracket.

Take down the bracket, then using a 6mm hand drill to make the two fixation holes on the wall you marked before.

Once the fixation holes are made, insert the two plastic wall anchors provided.

Use two ST4x20 crosshead screws to fix the wall-mounting bracket on the wall.


### With 86 embedded box in the wall



Make sure all cables in the 86 embedded box.

Fix the wall-mounting bracket on the 86 embedded box with two M4x30 crosshead screws.


## Device Mounting




After connecting the wires according to the wiring diagram, align the device with the wall-mounting bracket. And push down to fix the device securely.

# C313X Quick Guide

## Device Wiring



## Application Network Topology






NOTE: C313N does not have PON\_OUT Interface.

## Configuration




- 1.After setting up network and power, press **Status** icon to check IP address (DHCP by default).
- 2.Launch web browser and type in the IP address to access web interface, login with username and password.(admin by default).
- 3.Register the device with your SIP account.(please refer to user manual for more information).

## Operation

### Make a call

Press **Intercom** key  , enter the callee' s number or room address , then choose **Audio**   
or **Video**  mode to call out.


### Receive a call

When receiving a video call, users can choose **Audio**  or **Video**  mode to answer.  
However, if there is an audio call, users can only press **Audio**  mode to pick up.

### Unlock

During the talk, press the **Open Door** key **Open Door** in talking interface to unlock the door.

### Monitor

Press **Monitor** key  to receive the video from indoor IPC or community IPC any time.

### SOS

Press **SOS** key **SOS** in case of an emergency.



#### NOTICE:

Quick guide can be viewed on Global Visions website.

