

Akuvox: How to Setup Email Notifications on Door phones

Follow the steps to activate the Email Notification

PART 1: GETTING SMTP PASSWORD FROM GMAIL

Step 1: Navigate to your Google account settings





Step 3: Click the drop down for "Select App" and then select "Other". You can name this whatever you want.

Google Account		0	 Ð
	← App passwords		
	App passwords let you sign in to your Google Account from apps on devices that don't support 2-Step Verification. You'll only need to enter it once so you don't need to remember it. Learn more		
	You don't have any app passwords. Select the app and device you want to generate the app password for.		
	Select app v Select device v		
	GENERATE		
Privacy Terms Help About			

Step 4: Copy this password or write it down. You will use this in the email settings on the Akuvox WebUI.

	Your app password for your device			
	pghv wkmv vagi qdhw			
	How to use it			
Email	Go to the settings for your Google Account in			
securesally@gmail.com	the application or device you are trying to set			
Becoward	up. Replace your password with the 16-			
	Just like your normal password, this app			
••••	password grants complete access to your			
	Google Account. You won't need to remember			
	anyone.			
	,			

help@blvs.com



PART 2: AKUVOX WEB UI SETTINGS

Step 1: Log into your Akuvox Device web UI.

Step 2: Find the "Push Button Action" or "Call Event" section under the Intercom > Basic. Enable ""Email" for call notification then click "Submit"

Push	Button Action
action To Execute	FTP FTP Fmail HTTP
ITTP URL	
Submit	Cancel
	Call Event
Action To Execute FTP Em	ail 💙 HTTP 🗌

Step 3: Find the 'Action' setting. (Setting > Action or Intercom > Action)

Fill in settings. SMTP Server Address (for gmail): smtps://smtp.gmail.com. SMTP User Name is your gmail account. STMP Password is the password you created in Step 4.

Aku	/ох			
► Status	Action		Help	
▼ Intercom		Note:		
Basic User	Sender's Email Address	akuvoxtech@gmail.com	Max length of characters for input box:	
Schedule	Receiver's Email Address	email@gmail.com	255: Broadsoft Phonebook server address	
Card Setting	SMTP Server Address	smtps://smtp.gmail.com	127: Remote Phonebook URL & AUTOP Manual Update Server URL	
PIN Setting	SMTP User Name	akuvoxtech@gmail.com	63: The rest of input boxes	
LED Setting	SMTP Password	****	Warning:	
Relay	Email Subject	Akuvox Call	Field Description: Submit Shortcut	
Wiegand	Email Content	Someone has called you.		
Live Stream			Submit Cancel	
RTSP	Email Test	Email Test		
ONVIF		FTP Notification		
Motion	FTP Server			
Action HTTP API	FTP User Name			
Lift Control	FTP Password	******		

Once you've filled out the information click Submit.

Click this button for more resources ↓

Back to Global Visions Akuvox Knowledge Base

